

Steps to configure kit specifications in Acumatica inventory

- 1. Navigate to the search bar in Acumatica and type the keyword Kit Specifications.
- 2. Select **Kit Specifications** from the displayed search results.

• Acumatica	kit specifications	୰		Revision Two Products Products Wholesale	5/29/2023 9:16 AM	0	•
☆ Favorites	MENU ITEMS (1)	TRANSACTIONS AND PROFI	LES HELP TOPICS	FI	ILES	×	romiz
🕒 Data Views	🖙 Inventory						
Bills of Material	Profiles Kit Specifications						10difie
Time and Expenses	rat opecations						2023
Finance							323 2023
\$ Banking							2023 2023
Projects							2023
Payables							2023
							2023
Receivables		G					
🕉 Customization							
Sales Orders							
D - .							

Search for Kit Specifications

3. Click the **Selector** icon, enter the **KIT Inventory ID (Product Name)** to choose a product from the inventory.





	Acumatica	Search	Q	හ				Revision Two Products Whole	Products sale	5/29 9:20	/2023 АМ 🖌	0 🚨
	☆ Favorites	Kit Specification	ıs						NOTE:	ACTIN	ITIES FILES	CUSTOMIZA
×	🕒 Data Views	i⊐ ∽ +	і р. к	< > >I								
	Bills of Material	* Kit Inventory ID: CR	RICKET P	Active				1				
	Time and Expenses	* Revision: Description:	SELECT 🖒 🛏	4			ρ					
	Finance		Inventory ID 1	Description	Item Class	Item Status	Туре					
	\$ Banking	B Component ID		Cricket KIT Cutlery Product	CHARGABLE DISTRIB	Active Active	Charge Service	Min. ponent Cor	Max. Dis	assembly Coeff.	Allow Component	
	Projects		ELECOMP1 ELECOMP2	Dell desktop computer Lenovo laptop computer	ELECCOMP -400 ELECCOMP -400	Active	Finished G Finished G	Qity.	Qty.		Substitution	
	Payables		ELECRICKIT FACE BRIGHTENI	Electric KIT FACE BRIGHTENING KIT	CHARGE OPERATIONS	Active	Charge Non-Stock					
	Receivables		FIRST AID KIT	First Aid KIT Bundled Food Package 1	CHARGABLE	Active Active	Charge Non-Stock					
	🔅 Customization		GIFTHAMPER	Gift Hamper KIT 2	INTERNAL	Active Active	Service Non-Stock					
	Sales Orders		KIT 4 MECKIT	Cricket KIT	CHARGABLE	Active	Charge					
	~		PRINTCARDS	Print Cards	CHARGE	Active	Charge					

Product search using selector

- 4. Check the box provided against the **Customizable Kit**, this enables the non-stock items to be accessible and customizable.
- 5. Check the box provided against the **Not to Explode on API Sync**, this stops child items from exploding on price when the product explodes.

Note:

- $\circ~$ In Acumatica, API synchronization is the process of exchanging data between Acumatica and external systems or applications.
- When the **"Not to Explode on API Sync"** option is enabled or checked, it indicates that the child items associated with the parent product should not be automatically have their prices adjusted when the parent product is synchronized or updated through the API.
- This option is useful in scenarios where you want to maintain the original pricing and composition of the child items, even if changes are made to the parent product during API synchronization. By selecting this option, you can ensure that the child items remain unaffected by any updates or changes to the parent product's configuration, specifically in terms of pricing.





	Q Acumatica	Search	<u>م</u> ی						Re Pn	evision Two Proc oducts Wholesale
	Savorites	Kit Specificati	ons							E
×	Data Views	B ∽ +	D · K K	> >I						
	Bills of Material	* Kit Inventory ID:	ELECRICKIT - Electr P P	Active	Note		Customizable Kit	API Sync	components.	
	Time and Expenses	Description:	• •		(total		and the second s		components	li
	Finance			ENTS						
	\$ Banking	Component ID	Description	*UOM	Component Qty.	Allow Component Oty Variance	Min. Component Qty	Max. Component Qtv	Disassembly Coeff.	Allow Component Substitution
	Projects	SCREW DRI	Screw Driver	EA	4.00		4.00	10.00	1.000000	٥
	0	HAMMER	Hammer	EA	2.00		2.00	15.00	1.000000	
	Payables	TESTER	Tester	EA	2.00		2.00	8.00	1.000000	

Enable options on Kit Specifications

6. Under Stock Components, choose the Component ID and enter the Min and Max quantity.
• The permitted update quantity should be between the set variance Min and Max values.

Min and Max Quantity



7. Under Non-Stock Components, check the box labeled "Allow Component Quantity Variance."

Note:

 $\circ\,$ When this option is enabled, it permits flexibility in the component quantities used during kit assembly or Bill of Material (BOM) production.





Kit Specifications

* Kit Inventory ID	ELECRICKIT - Electr A	2 Active				Customizable Kit	
	Non-Stock	Z Allow	Component Additio	n		Not to Explode on API Sync	
* Revision:	1 P			Note:	P	rice will be the Sum total of child cor	mponents
Description:							
STOCK COMP		COMPONENTS					
STOCK COMP		COMPONENTS		5.7			

Configure kit components for non-stock items

